



分電盤リスト(1)																																	
盤名称	主開閉器	回路番号	分岐開閉器				リモコン リレー	容量 [VA]	備考	盤名称	主開閉器	回路番号	分岐開閉器				リモコン リレー	容量 [VA]	備考	盤名称	主開閉器	回路番号	分岐開閉器				リモコン リレー	容量 [VA]	備考				
			MCB1P 50/20	MCB2P 50/20	ELB2P 30/20	その他							MCB1P 50/20	MCB2P 50/20	ELB2P 30/20	その他							MCB1P 50/20	MCB2P 50/20	ELB2P 30/20	その他							
電灯盤 1L-1 屋内自立形 箱体：銅板製 塗装：標準色 国交省仕様		a		○				130	誘導灯	1L-1-2		A					200V ELCB2P30A	5800	100+100'ヒーター	電灯盤 2L-1 屋内壁掛形 箱体：銅板製 塗装：標準色 国交省仕様		a		○					50	誘導灯			
		b		○				100	複合受電機			B					200V ELCB2P30A	5800	100+100'ヒーター			101		○					260	非常照明			
		c		○				100	防災アンプ			C					200V ELCB2P30A	5800	100+100'ヒーター			102		○					7	799			
						MCB 3P 50A/ 50A		9560	電灯分電盤 1L-2			D					200V ELCB2P30A	5800	100+100'ヒーター			103		○					2	81			
						MCB 3P 50A/ 50A		8100	電灯動力盤 1LM-1						○		200V		予備			104		○							1180		
		101		○				380	非常照明						○		200V		予備			105		○					1	684			
		102		○				5	220			電灯						(23200)							○							予備	
		103		○				2	296			電灯				1		○				1600	オプ'ンレンジ			○						予備	
		104		○					1680			ロフト				2		○				1600	オプ'ンレンジ			○						予備	
		105		○					745			ロフト				3		○				1600	オプ'ンレンジ			○						(3004)	
		106		○					350			電灯				4		○				1600	オプ'ンレンジ			○						201	
		107		○					801			電灯				5		○				1100	食洗器・調理台コンセント			○					4	775	
		108				○			1							6		○				1100	食洗器・調理台コンセント			○					6	1310	
						○										7		○				1100	食洗器・調理台コンセント			○					3	488	
																8		○				1100	食洗器・調理台コンセント			○						204	
																							予備			○						205	
																							予備			○						206	
																							予備			○						207	
																							予備			○						208	
																							予備			○						209	
																							予備			○						210	
																							予備			○						211	
																							予備			○						212	
																							予備			○						213	
																							予備			○							
																							(6825)										301
																							400	コンセント			○						302
																							400	コンセント			○						303
																							500	コンセント			○						304
																							500	コンセント			○						305
																							400	コンセント			○						306
																							300	コンセント			○						307
																							500	コンセント			○						308
																							500	コンセント			○						309
																							500	コンセント			○						310
																							500	コンセント			○						311
																							500	コンセント			○						312
																							500	コンセント			○						313
																							800	コンセント			○						314
																							200	コンセント			○						315
																							200	コンセント			○						316
																							200	コンセント			○						317
																							200	コンセント			○						318
																							200	コンセント			○						319
																							300	コンセント			○						320
																	400	コンセント			○						321						
																	300	コンセント			○						322						
																	100	コンセント			○						323						
																	600	コンセント			○						324						
																	400	コンセント			○						325						
																	100	コンセント			○						326						
																	800	コンセント			○						327						
																	500	コンセント			○						328						
																	600	コンセント			○						329						
																	600	コンセント			○						330						
																	200	コンセント			○						331						
																	200	コンセント			○						332						
																	100	コンセント			○						333						
																	1000	コンセント			○						334						
																	300	コンセント			○						335						
																	1000	コンセント			○						336						
																	400	コンセント			○						337						
																	200	コンセント			○						338						
																		予備			○												
																		予備			○												
																	(16500)																
																											401						
																											402						
																											403						
																											404						